



Internal Collection Dynamic Application (ICDA) Development

SL1 version 8.10.0

Table of Contents

Introduction to Internal Collection Dynamic Applications (ICDAs)	3
What is an Internal Collection Dynamic Application?	4
How Do ICDAs Work?	4
Types of ICDAs	5
Snippets and Execution Environments	6
Data Collected by ICDAs	6
Internal Collection Inventory Application Types	6
Filesystem Inventory	6
Interface Inventory	7
Internal Collection Inventory Application Types	7
Availability	7
SNMP Detail	8
Filesystem Performance	8
Interface Performance	8
Port Performance	8
Process Inventory	9
Process Performance	9
Service Inventory	9
Service Performance	10
Creating Internal Collection Dynamic Applications	11
Viewing the List of ICDAs	12
Creating an ICDA	12
Creating a Container for the ICDA Snippet	14
Creating the Collection Objects	16
Adding the Snippet Code	17
Snippet Examples for ICDAs	17
Availability	17
Discovery	18
Filesystem Inventory	18
Filesystem Type	19
Interface Octets	20
Latency	20

Introduction to Internal Collection Dynamic Applications (ICDAs)

Overview

This manual describes how to use Internal Collection Dynamic Applications (ICDAs) to gather data from devices that do not support SNMP or to perform customized processing on collected SNMP data.

This manual does not cover elements of Dynamic Application development that are common to all Dynamic Application types. You should be familiar with the common elements and concepts of Dynamic Applications before reading this manual. For general information on planning, designing, using, and troubleshooting Dynamic Applications, see the manual *Dynamic Application Development*.

This manual contains the following topics:

<i>What is an Internal Collection Dynamic Application?</i>	4
<i>How Do ICDAs Work?</i>	4
<i>Types of ICDAs</i>	5
<i>Snippets and Execution Environments</i>	6
<i>Data Collected by ICDAs</i>	6
<i>Internal Collection Inventory Application Types</i>	6
<i>Internal Collection Inventory Application Types</i>	7

What is an Internal Collection Dynamic Application?

The ScienceLogic platform has traditionally used SNMP and an internal process called "internal collection" to collect the following data for each device:

- Availability and latency
- System description, system uptime, and system local
- Filesystem inventory and performance
- Interface inventory and performance

However, you might need to monitor device data that is partially available through SNMP, or not available at all through SNMP.


For devices that do *not* support SNMP, the ScienceLogic platform provides an additional method to collect this data called **Internal Collection Dynamic Applications (ICDAs)**. ICDAs combine the efficiency of internal collection with the flexibility of dynamic applications, ensuring uniform data across the ScienceLogic platform.

How Do ICDAs Work?

Internal Collection Dynamic Applications align to devices in the same way as other Dynamic Applications. If the ICDA includes a discovery object, the ICDA automatically aligns with devices during discovery. You can also manually align ICDAs to devices and include ICDAs in device templates.

When the ScienceLogic platform begins an internal collection, it checks to see if any ICDAs are aligned. If ICDAs are aligned, the platform performs an "Extended Internal Collection". The platform combines data it collected using ICDAs with data it collected using an internal SNMP process, and then the platform completes the collection process.

The following illustration highlights the ICDA functionality in the collection process:



NOTE: If the ScienceLogic platform collects this data using the SNMP-based internal collection and also collects this data using ICDA, the data from ICDA, takes precedence.

The ICDA data that the ScienceLogic platform collects is stored in a database that is separate from the dynamic application database. ICDA results are stored where the corresponding internal collection would store its results.

ICDAs do not include presentation objects, thresholds, or alerts. The ScienceLogic platform evaluates alerts and events in exactly the same way as for standard internal collection.

Types of ICDA

There are two types of Internal Collection Dynamic Applications:

- **Internal Collection Inventory.** These ICDA collect configuration data about filesystems, such as storage size, filesystem type, and storage used. These ICDA also collect configuration data about interfaces, such as physical address, operational status, and IP addresses. In the ScienceLogic platform, the available Data Models for this Application Type are Filesystem Inventory and Interface Inventory.
- **Internal Collection Performance.** Collects data about availability and latency, device information (system description, system uptime, system local), filesystem performance, and interface performance. In the ScienceLogic platform, the available Data Models for this Application Type are Availability, Filesystem Performance, SNMP Detail (includes Uptime, Description, and Locale), and Interface Performance.

NOTE: The names for the ICDA Data Models follow the existing naming conventions used by the internal collection processes.

Snippets and Execution Environments

Internal Collection Dynamic Applications collect data by executing one or more blocks of Python code, called **snippets**. The ScienceLogic platform passes credential and other configuration information to the snippet, and at the end of execution, the snippet must pass collected data back to the platform. The Dynamic Application developer defines snippet code that collects data and processes data.

One way in which Dynamic Applications that use snippets are unique from most other types of Dynamic Applications is that they can be aligned with a specific execution environment.

An **execution environment** is an on-demand Python environment that includes the supporting modules, code, scripts, directories, and files (packaged in one or more ScienceLogic Libraries) needed to run a snippet. An execution environment includes its own installation directories, doesn't share libraries with other environments, and allows granular control of dependencies and versions.

When you create an Internal Collection Dynamic Application, you must select an execution environment to align with that Dynamic Application. All of the snippets contained in the Dynamic Application will then use that execution environment whenever the Dynamic Application runs. If you do not specify an execution environment, the ScienceLogic platform will align the Dynamic Application with the default *System* environment.

You can create and manage execution environments on the **Environment Manager** page (System > Customize > ScienceLogic Libraries > Actions > Execution Environments). For more information about creating and managing execution environments, see the **ScienceLogic Libraries and Execution Environments** manual.

Data Collected by ICDA

This section lists the collection objects included in each type of Data Model.

NOTE: For each Data Model, this list also describes how to index the collection objects so they can be merged with values from the internal, SNMP-based collection process. Ensure that you follow the indexing format. Improper indexing could result in duplicated entities if the two types of data cannot be merged.

The ICDA data takes precedence over any data collected during SNMP-based internal collection.

Internal Collection Inventory Application Types

Filesystem Inventory

Index: **Filesystem Name**, such as `/dev/sda1`.

Objects:

- **Storage Size.** Measured in storage units.
- **Filesystem Type.** Type of filesystem, such as ext4.
- **Storage Used.** Measured in storage units.
- **Storage Units.** Measured in bytes per storage units.
- **Media Type.** Type of media, such as CD, hard drive, or flash drive.

Interface Inventory

Index: SNMP interface index or user-defined unique index if only ICDA collects the data for the interface.

Objects:

- **Name.** String.
- **Alias.** String.
- **Descr.** String.
- **Type.** Interface type as defined in IF-MIB.
- **Phys Address.** String for the MAC Address.
- **Speed.** Measured in bps.
- **High Speed.** Measured in Megabits per second, or Mbps.
- **Admin Status.** Integer: up [1], down [2], testing[3].
- **Operational Status.** Integer: up [1], down [2], testing[3], unknown [4], dormant [5], not present [6], lower layer down [7].
- **Connector Present.** Integer.
- **64-bit Support.** True or false.
- **Blade.** Blade number.
- **Port.** Port number.
- **IP Addresses.** IP Address and Subnet, such as [(1.2.3.4, 255.255.255.0), (2.3.4.5, 255.255.255.128)].

Internal Collection Inventory Application Types

Availability

Index: None (this impacts the entire device, so there can only be only value per index).

Objects:

- **Availability.** True or false, depending on whether the device is available.
- **Latency.** Measures uptime in 10 millisecond increments.

SNMP Detail

Index: None (this impacts the entire device, so there can only be only value per index).

Objects:

- **System Description**. String.
- **System Uptime**. Measured in 10-millisecond increments.
- **System Locale**. String.

Filesystem Performance

Index: **Filesystem Name**, such as `/dev/sda1`.

Objects:

- **Storage Used**. Measured in storage units.
- **Storage Units**. Measured in bytes per storage units.
- **Percent Used**. Measured in percentage of storage used.

Interface Performance

Index: SNMP interface index or user-defined unique index if only ICDA collects data for the interface.

Objects:

- **Phys Address**. String for the MAC Address.
- **Admin Status**. Integer: up [1], down [2], testing[3].
- **Operational Status**. Integer: up [1], down [2], testing[3], unknown [4], dormant [5], not present [6], lower layer down [7].
- **ifInOctets**. Interface Inbound Traffic in octets.
- **ifOutOctets**. Interface Outbound Traffic in octets.
- **ifInDiscards**. Interface Inbound Discards.
- **ifOutDiscards**. Interface Outbound Discards.
- **ifOutErrors**. Interface Outbound Errors.
- **ifInErrors**. Interface Inbound Errors.

Port Performance

Index: Data pair of port number and port protocol: TCP (0), UDP (1)

Objects:

- **State**. Port state, up or down.

Process Inventory

NOTE: ICDA process data does not merge with agent-collected data.

Index: Process Pid number

Objects:

- **Name**. String for the Process Name.
- **Arguments**. String for the Process Arguments.
- **Path**. String for the Process Path.
- **User**. String for the Process User.
- **CPU Time**. Integer.
- **Memory Use**. Integer.
- **State**. Integer.

Process Performance

NOTE: ICDA process data does not merge with agent-collected data.

Index: Process Pid number

Objects:

- **Name**. String for the Process Name.
- **Arguments**. String for the Process Arguments.
- **Path**. String for the Process Path.
- **User**. String for the Process User.
- **CPU Time**. Integer.
- **Memory Use**. Integer.
- **State**. Integer.

Service Inventory

Index: Service Name

Objects:

- **Start Mode.** String: Auto, Manual, Disabled, Anything Else.
- **State.** Integer: 0 (running), 1 (not running).

Service Performance

Index: Service Name

Objects:

- **Start Mode.** String: Auto, Manual, Disabled, Anything Else.
- **State.** Integer: 0 (running), 1 (not running).

Creating Internal Collection Dynamic Applications

Overview

This chapter describes how to create and use create Internal Collection Dynamic Applications (ICDAs).

This chapter includes the following topics:

<i>Viewing the List of ICDAs</i>	12
<i>Creating an ICDA</i>	12
<i>Creating a Container for the ICDA Snippet</i>	14
<i>Creating the Collection Objects</i>	16
<i>Adding the Snippet Code</i>	17
<i>Snippet Examples for ICDAs</i>	17
<i>Availability</i>	17
<i>Discovery</i>	18
<i>Filesystem Inventory</i>	18
<i>Filesystem Type</i>	19
<i>Interface Octets</i>	20
<i>Latency</i>	20

Viewing the List of ICDA's

You can view all Internal Collection Dynamic Applications on the Dynamic Applications Manager page (System > Manage > Applications) by typing "Internal" in the **Type** filter-while-you-type field:

Dynamic Application Name	Poll Rate	Type	State	Version	ID	Subscribers	PowerPack	Environment	Collects	Alerts	Events	Thresh	Edited By	Last Edit
Availability Test ICDA	0 min.	Internal Collection Per	Enabled	1	1498	--	ScienceLogic: ICDA Hard	SYSTEM	2	--	--	--	em7admin	2018-07-22 09:45:29
Availability Test ICDA 2	0 min.	Internal Collection Per	Enabled	1	1506	--	ScienceLogic: ICDA Hard	SYSTEM	2	--	--	--	em7admin	2018-07-22 09:45:29
Cisco ACI Component Uptime	0 min.	Internal Collection Per	Enabled	0.5	1509	--	ICDA Sample Apps	ICDA Sample Apps	1	--	--	--	em7admin	2018-07-22 09:43:59
F5 Inv Test ICDA	0 min.	Internal Collection Inv	Enabled	1	1508	--	ScienceLogic: ICDA Hard	SYSTEM	5	--	--	--	em7admin	2018-07-22 09:45:29
F5 Inv Test ICDA 2	0 min.	Internal Collection Inv	Enabled	1	1503	--	ScienceLogic: ICDA Hard	SYSTEM	5	--	--	--	em7admin	2018-07-22 09:45:29
F5 Perf Test ICDA	0 min.	Internal Collection Per	Enabled	1	1501	--	ScienceLogic: ICDA Hard	SYSTEM	3	--	--	--	em7admin	2018-07-22 09:45:29
F5 Perf Test ICDA 2	0 min.	Internal Collection Per	Enabled	1	1504	--	ScienceLogic: ICDA Hard	SYSTEM	3	--	--	--	em7admin	2018-07-22 09:45:29
ICDA Filesystem	0 min.	Internal Collection Inv	Enabled	0.5	1510	--	ICDA Sample Apps	ICDA Sample Apps	2	--	--	--	em7admin	2018-07-22 09:43:59
ICDA Interface Performance	0 min.	Internal Collection Per	Enabled	0.1	1511	--	ICDA Sample Apps	ICDA Sample Apps	1	--	--	--	em7admin	2018-07-22 09:43:59
ICDA Latency	0 min.	Internal Collection Per	Enabled	0.1	1512	--	ICDA Sample Apps	ICDA Sample Apps	1	--	--	--	em7admin	2018-07-22 09:43:59
IF Inv Test ICDA	0 min.	Internal Collection Inv	Enabled	1	1500	--	ScienceLogic: ICDA Hard	SYSTEM	14	--	--	--	em7admin	2018-07-22 09:45:29
Interface Perf Test ICDA	0 min.	Internal Collection Per	Enabled	1	1507	--	ScienceLogic: ICDA Hard	SYSTEM	5	--	--	--	em7admin	2018-07-22 09:45:29
Interface Perf Test ICDA 2	0 min.	Internal Collection Per	Enabled	1	1499	--	ScienceLogic: ICDA Hard	SYSTEM	2	--	--	--	em7admin	2018-07-22 09:45:29
Interface Perf Test ICDA 2	0 min.	Internal Collection Per	Enabled	1	1505	--	ScienceLogic: ICDA Hard	SYSTEM	7	--	--	--	em7admin	2018-07-22 09:45:29
SNMP Detail Test ICDA 1	0 min.	Internal Collection Per	Enabled	1	1496	--	ScienceLogic: ICDA Hard	SYSTEM	3	--	--	--	em7admin	2018-07-22 09:45:29
SNMP Detail Test ICDA 2	0 min.	Internal Collection Per	Enabled	1	1497	--	ScienceLogic: ICDA Hard	SYSTEM	1	--	--	--	em7admin	2018-07-22 09:45:29

TIP: To ensure the consistency of your data, do not use an ICDA to collect data on a device that was previously monitored by another type of Dynamic Application.

Creating an ICDA

You can create custom Internal Collection Dynamic Applications (ICDA's) to gather data on devices that do not support SNMP. Currently, ICDA's support only the **snippet** protocol.

NOTE: If you create an ICDA with a Data Model of *Interface Inventory* and the ICDA includes a discovery Collection Object, the ICDA aligns with the device after the platform discovery runs. As a result, the platform does not discover interfaces until either the nightly discovery runs or the user re-discovers the device manually by running the discovery session again, creating a new discovery session, or initiating an ad hoc discovery.

To create an ICDA:

1. Go to the **Dynamic Applications Manager** page (System > Manage > Applications).

- Click the **[Actions]** button and select *Create New Dynamic Application*. The **Dynamic Applications Create New Application** page appears.

The screenshot shows the 'Dynamic Applications | Create New Application' form. The 'Application Type' dropdown is highlighted with a red box and set to 'Internal Collection Performance [27]'. Other fields include Application Name, Version Number, Operational State, Abandon Collection, Context, Caching, Device Dashboard, Collector Affinity, Poll Frequency, Maximum Devices, Null Row Option, Null Column Option, Disable Rollup of Data, and Component Mapping. A 'Save' button is visible at the bottom right.

2

- Complete the following fields:
 - Application Name.** Type a name for this ICDA.
 - Application Type.** Your options for ICDA's include *Internal Collection Inventory* or *Internal Collection Performance*.
- Click the **[Save]** button. The **[Properties]** tab updates to show the relevant fields for the ICDA:

The screenshot shows the 'Dynamic Applications [1588] | Application Successfully Created | Properties Editor' form. The 'Application Name' is 'Interface Performance', 'Application Type' is 'Internal Collection Performance', 'Execution Environment' is 'Default Environment', and 'Data Model' is 'Availability'. The 'Version Number' is 'Version 1.0' and 'Operational State' is 'Enabled'. 'Save' and 'Save As' buttons are visible.


5. In the **Execution Environment** drop-down list, select the execution environment to which you want to align the Dynamic Application. An execution environment is an on-demand Python environment that includes the supporting modules, code, scripts, directories, and files (packaged in one or more ScienceLogic Libraries) needed to run a snippet. An execution environment includes its own installation directories, doesn't share libraries with other environments, and allows granular control of dependencies, versions, and permissions. The default execution environment is *System*. For more information, see the **ScienceLogic Libraries** manual.
6. In the **Data Model** drop-down list, select the type of data you want to collect with this ICDA. The values in the drop-down are dependent on the value in the **Application Type** field. The value in the **Data Model** field list determines the available options in the **Object Link** drop-down list on the **[Collections]** tab. For example, if you select *Availability* for the Data Model, then you can choose only *Availability* or *Latency* in the **Object Link** drop-down list.
 - If you selected *Internal Collection Inventory* as the **Application Type**, the **Data Model** drop-down includes:
 - **Filesystem Inventory**. Monitors Storage Size, Filesystem Type, Storage Used, Storage Units, or Media Type.
 - **Interface Inventory**. Monitors Name, Alias, Description, Type, Physical Address, Speed, High Speed, Admin Status, Operational Status, Connector Present, 64-bit Support, Blade, Port, or IP Address.
 - If you selected *Internal Collection Performance* as the **Application Type**, the **Data Model** drop-down includes:
 - **Availability**. Monitors Availability or Latency.
 - **Filesystem Performance**. Monitors Storage Used, Storage Units, or Percentage Used.
 - **SNMP Detail**. Monitors System Description, System Uptime, or System Locale.
 - **Interface Performance**. Monitors Octets In, Octets Out, Errors In, Errors Out, Discards In, Discards Out, Physical Address, Admin Status, or Operational Status.
7. Update the remaining fields as needed, and then click the **[Save]** button.
8. Next, create a container for your ICDA snippet code.

Creating a Container for the ICDA Snippet

In Snippet Dynamic Applications, each collection object must be associated with a snippet. Therefore, in ICDAs you must create the container for the snippet code before creating the collection objects for this ICDA.

To create a container for the snippet code:

1. Click the **[Snippets]** tab.



2. Complete the following fields:


- **Snippet Name.** The name of the snippet.
- **Active State.** Specifies whether the snippet should be executed by the ScienceLogic platform when performing collection for the ICDA.
- **Required.** Specifies whether this snippet is required for successful collection of all other snippet requests. Choices are:
 - *Required - Stop Collection.* If this snippet request fails, the platform will not attempt to execute any other snippet requests in this ICDA. Dynamic Applications that consume the cache of this ICDA will halt collection.
 - *Not Required - Continue Collection.* If this snippet request fails, the platform will continue executing all remaining snippet requests in this ICDA. Dynamic Applications that consume the cache of this ICDA will continue collection.
- **Snippet Code.** The python code that will be executed when the ScienceLogic platform performs collection for this ICDA. You will add the snippet code later.

3. Click the **[Save]** button.
4. Repeat this process for each collection you want to use in conjunction with a snippet.
5. Next, create the collection objects for your ICDA.

Creating the Collection Objects

To create the collection object or objects for this ICDA:

1. Click the **[Collections]** tab.



The screenshot shows a software interface for configuring collection objects. The window title is "Dynamic Applications [1908] | Collection Objects". It features a tabbed interface with "Collections" selected. The configuration form includes the following fields:

- Object Name:** Performance Uptime
- Snippet Arguments:** (Empty text box)
- Class Type:** [33] ICDA Object
- String Type:** [Standard]
- Object Link:** [16] System Uptime
- Snippet:** Performance Uptime
- Description:** (Empty text area)
- Formula:** (Empty text area)


At the bottom of the form, there is a "Save" button and a checkbox labeled "Disable Object Maintenance". The main content area below the form displays the message: "There are no collection objects for this application."

2. Complete the following fields to create the collection object:
 - **Object Name.** Type the name of the collection object.
 - **Snippet Arguments.** Specify any arguments you want to pass to the snippet.
 - **Class Type.** Depending on the type of collection object you want to create, select *[33] ICDA Object* or *[100] Discovery*.
 - **String Type.** Define the string type for this snippet. Select *Standard* or *Hex Code*.
 - **Object Link.** Select the specific type of data you want to collect with this ICDA. The options in this drop-down list are based on your selection for the **Data Model** field on the **[Properties]** tab.
 - **Snippet.** Select the name of the snippet you created in the previous process.
3. Update the remaining fields as needed, and then click the **[Save]** button.
4. Repeat these steps to create additional collection objects you want to use in conjunction with a snippet.
5. Next, add the snippet code for your new ICDA.

Adding the Snippet Code

To add the snippet code to a new ICDA:

1. Click the **[Snippets]** tab.
2. In the **Snippet Registry** pane, select the relevant snippet and click its wrench icon (🔧). Information about that snippet appears in the top pane:



3. In the **Snippet Code** field, type or paste your python code for the collection object.
4. Click the **[Save]** button and close the modal page for the ICDA.

Snippet Examples for ICDA

The following snippets were created by ScienceLogic to use as sample snippets for ICDA.

Availability

```

from silo_builtin_caching import get_cached_request_result
Windows_Server_Uptime_REQ_GUID = '32CA377A59190A6AB83DC5EDB05CA7E7'
result = {
    'if': get_cached_request_result(self, Windows_Server_Uptime_REQ_GUID)
}
print "*****"
print result

for grp_id, grp in self.oids.iteritems():
    for obj_id, obj in grp.iteritems():
        try:
    
```

```

        (req, oid) = obj['oid'].split('.')
        result_list = result[req].get(oid, {}).values()

    except ValueError:
        self.logger.ui_debug('Skipping OID %d' % obj_id)
        continue
    if len(result_list) >= 1 and float(result_list[0]) > 0.0:
        obj['result'] = [(0, True)]

    #obj['result'] = [(0, True if len(result_list) >= 1 and float(result_list[0]) >
    0.0 else False)]
    print obj

```

Discovery

```

from silo_common.global_definitions import CRED_SSH

import paramiko

if self.cred_details['cred_type'] == CRED_SSH:
    host = self.cred_details['cred_host']
    user = self.cred_details['cred_user']
    passwd = self.cred_details['cred_pwd']
    timeout = self.cred_details['cred_timeout'] / 1000
    port = self.cred_details['cred_port']

    ssh = paramiko.SSHClient()
    ssh.set_missing_host_key_policy(paramiko.AutoAddPolicy())

    ssh.connect(host, username=user, password=passwd, port=port, timeout=timeout)
    stdin, stdout, stderr = ssh.exec_command("uname")
    os = stdout.readlines()
    if os[0].startswith("Linux"):
        result_handler['disc'] = True
    ssh.close()
else:
    self.logger.debug("ICDA Filesystem | DID %s: Incorrect credential type aligned, must
    be SSH" % self.did)

```

Filesystem Inventory

```

from silo_builtin_caching import get_cached_request_result
import re

#Enum to translate drive type to string
FS_ENUM_TYPES={
    0: 'Unknown',
    1: 'No Root Directory',
    2: 'Removable Disk',
    3: 'Local Disk',
    4: 'Network Drive',
    5: 'Compact Disc',
    6: 'RAM Disk'
}

result = get_cached_request_result(self, WINDOWS_SERVER_DISK_CONFIGURATION_REQ_GUID)

```

```

indexes = set()
units_object = {}

for grp_id, grp in self.oids.iteritems():
    for obj_id, obj in grp.iteritems():
        oid = obj['oid']
        result_list = result.get(oid, {}).items()

        #Keep track of all the indexes (which are the filesystem names)
        #Rewrite the results list to clean up filesystem names
        for (i, (k, v)) in enumerate(result_list):
            #An empty string index will attempt to use the label first,
            #and fall back to " " if there is no label
            if k == '':
                k = result.get('label', {}).get('', ' ')
                result_list[i] = (k, v)
            #Add a backslash to drive letters to match the output from SNMP
            elif re.match('[A-Z]:$', k):
                k += '\\\ '
                result_list[i] = (k, v)
            indexes.add(k)

        #If this is the 'units' object, set it aside for later processing
        if obj['oid'] == 'units':
            units_object = obj
            continue

        #Translate the drivetype enum to a string
        if obj['oid'] == 'drivetype':
            result_list = [(index, FS_ENUM_TYPES.get(int(value), value)) for index, value in
                result_list]

        obj['result'] = result_list

#Do the processing for the units object (all units are 1 - bytes)
units_object['result'] = [(i, 1) for i in indexes]

```

Filesystem Type

```

from silo_common.global_definitions import CRED_SSH
import paramiko
if self.cred_details['cred_type'] == CRED_SSH:
    host = self.cred_details['cred_host']
    user = self.cred_details['cred_user']
    passwd = self.cred_details['cred_pwd']
    timeout = self.cred_details['cred_timeout'] / 1000
    port = self.cred_details['cred_port']

    ssh = paramiko.SSHClient()
    ssh.set_missing_host_key_policy(paramiko.AutoAddPolicy())
    ssh.connect(host, username=user, password=passwd, port=port, timeout=timeout)

    stdin, stdout, stderr = ssh.exec_command("df --output=target,fstype",
        timeout=timeout)

    results = []
    lines = stdout.readlines()[1:]
    for line in lines:
        fs_name, fs_type = map(lambda line: line.strip(), line.split(' ', 1))
        results.append((fs_name, fs_type))

```

```

    result_handler['fs_type'] = results
    ssh.close()
else:
    self.logger.debug("ICDA Filesystem | DID %s: Incorrect credential type aligned, must
    be SSH" % self.did)

```

Interface Octets

```

from silo_common.credentials import snmph_from_cred_array
from silo_common.exceptions import SnmpError

OID_ifInOctets = '.1.3.6.1.2.1.2.2.1.10'

results = []
try:
    snmp_h = snmph_from_cred_array(self.cred_details, self.ip)
    octets_in_walk = snmp_h.walk(OID_ifInOctets)

    for oid, value in octets_in_walk:
        if_index = oid.split('.')[1]
        # offset to make this differentiable from the value returned by normal internal
        collection
        if_in_octets = int(value) + 100000
        results.append((if_index, if_in_octets))
except SnmpError, err:
    self.logger.ui_debug("An SNMP error occurred during interface performance
    collection")
finally:
    result_handler['ifInOctets'] = results

```

Latency

```

from silo_collect.tools import latency_ping
from silo_common.network import ip

ip_obj = ip(self.ip)

# add large offset to make ICDA data stand out
result_handler['latency'] = [('0', latency_ping(ip_obj, logger=self.logger) + 5000)]

```

© 2003 - 2018, ScienceLogic, Inc.

All rights reserved.

LIMITATION OF LIABILITY AND GENERAL DISCLAIMER

ALL INFORMATION AVAILABLE IN THIS GUIDE IS PROVIDED "AS IS," WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED. SCIENCELOGIC™ AND ITS SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT.

Although ScienceLogic™ has attempted to provide accurate information on this Site, information on this Site may contain inadvertent technical inaccuracies or typographical errors, and ScienceLogic™ assumes no responsibility for the accuracy of the information. Information may be changed or updated without notice. ScienceLogic™ may also make improvements and / or changes in the products or services described in this Site at any time without notice.

Copyrights and Trademarks

ScienceLogic, the ScienceLogic logo, and EM7 are trademarks of ScienceLogic, Inc. in the United States, other countries, or both.

Below is a list of trademarks and service marks that should be credited to ScienceLogic, Inc. The ® and ™ symbols reflect the trademark registration status in the U.S. Patent and Trademark Office and may not be appropriate for materials to be distributed outside the United States.

- ScienceLogic™
- EM7™ and em7™
- Simplify IT™
- Dynamic Application™
- Relational Infrastructure Management™

The absence of a product or service name, slogan or logo from this list does not constitute a waiver of ScienceLogic's trademark or other intellectual property rights concerning that name, slogan, or logo.

Please note that laws concerning use of trademarks or product names vary by country. Always consult a local attorney for additional guidance.

Other

If any provision of this agreement shall be unlawful, void, or for any reason unenforceable, then that provision shall be deemed severable from this agreement and shall not affect the validity and enforceability of any remaining provisions. This is the entire agreement between the parties relating to the matters contained herein.

In the U.S. and other jurisdictions, trademark owners have a duty to police the use of their marks. Therefore, if you become aware of any improper use of ScienceLogic Trademarks, including infringement or counterfeiting by third parties, report them to Science Logic's legal department immediately. Report as much detail as possible about the misuse, including the name of the party, contact information, and copies or photographs of the potential misuse to: legal@sciencelogic.com



800-SCI-LOGIC (1-800-724-5644)

International: +1-703-354-1010