



Aruba Central PowerPack Release Notes

Version 200.1

Overview

Version 200.1 of the *Aruba Central* PowerPack addresses an issue with OAuth2 authentication that prevented proxy credentials from functioning correctly.

- **Minimum Required SL1 Version:** 12.1.0

This document covers the following topics:

<i>Before You Install or Upgrade</i>	2
<i>Installing or Upgrading the PowerPack</i>	2
<i>Features</i>	4
<i>Enhancements and Issues Addressed</i>	4
<i>Known Issues</i>	4

Before You Install or Upgrade

Ensure that you are running version 12.1.0 or later of SL1 before installing "Aruba Central" PowerPack version 200.1.

NOTE: For details on upgrading SL1, see the relevant [SL1 Platform Release Notes](#).

TIP: If you are currently using a version prior to 103 of this PowerPack, a direct upgrade to version 200 is not supported and a fresh install and re-discovery of devices may be required with version 200. Versions 103, 104, and 104.1 can be upgraded directly to version 200 if there is only one DCM tree discovered per Aruba Central account. If separate API keys are being used to discover sites individually as their own DCM tree, a fresh install and re-discovery is also required. The steps for both methods can be found below and in the *Monitoring Aruba Central* manual. Follow those procedures to ensure accurate data collection post upgrade.

Installing or Upgrading the PowerPack

TIP: By default, installing a new version of a PowerPack will overwrite all content in that PowerPack that has already been installed on the target system. You can use the **Enable Selective PowerPack Field Protection** setting in the **Behavior Settings** page (System > Settings > Behavior) to prevent the new version of the PowerPack from overwriting local changes for some commonly customized fields.

NOTE: If you are currently using the Dynamic Applications in this PowerPack to monitor devices, collection errors might occur for one or two polling cycles during the installation of a new version. To prevent collection errors during an upgrade, you can optionally disable collection for monitored devices before performing the following steps and re-enable collection after the upgrade.

NOTE: If you are currently using the Dynamic Applications in this PowerPack to monitor devices, collection errors might occur for one or two polling cycles during the installation of a new version. To prevent collection errors during an upgrade, you can optionally disable collection for monitored devices before performing the following steps and re-enable collection after the upgrade.

To install this PowerPack:

1. Search for and download the PowerPack from the **PowerPacks** page (Product Downloads > PowerPacks & SyncPacks) at the [ScienceLogic Support Site](#).
2. In SL1, go to the **PowerPacks** page (System > Manage > PowerPacks).
3. Click the **Actions** menu and choose *Import PowerPack*. The **Import PowerPack** modal appears.
4. Click **[Browse]** and navigate to the PowerPack file from step 1.
5. Select the PowerPack file and click **[Import]**. The **PowerPack Installer** modal displays a list of the PowerPack contents.
6. Click **[Install]**. The PowerPack is added to the **PowerPack Manager** page.

After upgrading the PowerPack to version 200, follow the steps below:

1. Disable the listed Dynamic Applications.
 - Aruba: Central AP Container Discovery
 - Aruba: Central SD-WAN Gateway Container Discovery
 - Aruba: Central Switch Container Discovery

NOTE: For instructions on disabling Dynamic Applications, see the section on "Performing Other Tasks in the Dynamic Application Manager Page" in the *Dynamic Application Development* manual.

2. Disable the listed container device components.
 - AP Container
 - SD-WAN Gateway Container
 - Switch Container
3. Apply the new Aruba template included in this version of the PowerPack to the root virtual device. This will cause devices to move from the container component devices to sites.

NOTE: For instructions on applying a template, see the "Aligning the Device Template to Your Aruba Central Virtual Device" section in the *Monitoring Aruba Central* manual.

4. Once all components have been migrated to sites, remove the empty container device components listed in step 2.
5. Delete the disabled Dynamic Applications listed in step 1.

For instructions on using the PowerPack, see the *Monitoring Aruba* manual.

Features

This release includes the following features:

- Dynamic Application to discover and monitor Aruba Central component devices
- Device Classes for each of the Aruba Central components that the PowerPack can monitor
- Event Policies that are triggered when Aruba Central component devices meet certain status criteria
- A sample SOAP/XML Credential ("Aruba Central Example") that you can use to create your own Aruba Central Credential
- A Device Template ("Aruba Central Template") that aligns Dynamic Applications to the Aruba Central controller virtual device and enables you to discover component devices for that controller
- Device Dashboards that display information about Aruba Central component devices
- A sample SOAP/XML Credential (Aruba Central SSO Example) that can be used to create an Aruba Central SSO Credential.

Enhancements and Issues Addressed

The following enhancements and addressed issues are included this release of the "Aruba Central" PowerPack:

- Addressed an issue with OAuth2 authentication that prevented proxy credentials from functioning correctly.

Known Issues

The following known issues affect version 200.1 of the *Aruba Central* PowerPack:

- The "Aruba: Central AP Discovery" Dynamic Application will be disabled after install of version 200 of this PowerPack regardless of the PowerPack Field Protection setting for this Dynamic Application.
- An additional "Aruba Central Example" and/or "Aruba Central SSO Example" credential may be created when upgrading to version 200 from a version prior to version 104.1.
- The following widgets will not display data for the "Aruba: Central Controller," "Aruba: Wireless Access Points," "Aruba: Gateway Summary," "Aruba: Gateway," and "Aruba: Switches" SL1 dashboards because the

Dynamic Applications "REST: Performance Metrics Monitor (Aruba Central)" is disabled by default for this version:

- Requests (avg)
- Latency-Maximum, Minimum, Average (avg)
- SLL and Connection Errors (avg)
- Timeout (avg)
- Total Components
- AP Count
- Switch Count
- Gateway Count

Additionally, the following widgets on the "Aruba: Central Controller" Device Dashboard included in the PowerPack will not display data:

- Total Requests sent from EM7 to Aruba Central
- Error Response Count (Errors received back from Aruba Central)
- Total Access Points
- Total Switches
- Total Gateways
- A non-numeric value API-response, for the "Aruba: Central Switch Performance" collection objects, generates too many system log entries. An error message reads "Non-digits in oid with object id: <object_id>, did: <device_id> in dynamic app: <app_id> when updating performance value (val:-)". However, this does not affect data collection.
- Vitals metrics are displaying unusual labels for CPU and Memory Utilization metrics in the "Aruba: Central SD-WAN Gateway Performance" and "Aruba: Central Switch Performance" Dynamic Applications.
- An exception will be logged when the **Embed Value [%4]** field, in the credential, is left empty, contains a non-numeric value, or contains a value less than or equal to 0. SIGTERMS could be present on system logs as well.
- By default, configuration Dynamic Applications are set to display "Last Collected" data if a poll is missed. If you would like for the most recent value to display, set "--values" for the "Null Column Option" property.
- A known issue might cause Dynamic Application debug mode to fail in the SL1 user interface. To troubleshoot Dynamic Applications in version 104, ScienceLogic recommends using the command line debug mode on the Data Collector.
- The error messages for a device, during data collection, will not display on Device Logs, but device error messages will print on log files.
- A known issue causes Dynamic Applications to display information on reports even if the user credential has an incorrect username and password when a session was previously generated with valid credentials. This behavior will continue until the refresh token expires.

- The tokens generated from the API Gateway UI in Aruba Central during SSO authentication are available for 15 days, and if not refreshed within that period, it will be revoked and all collection will stop. To restart collection, you must generate a new refresh token in Aruba Central and include it in the SOAP/XML credential (***EmbedValue[%2]***).

© 2003 - 2024, ScienceLogic, Inc.

All rights reserved.

LIMITATION OF LIABILITY AND GENERAL DISCLAIMER

ALL INFORMATION AVAILABLE IN THIS GUIDE IS PROVIDED "AS IS," WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED. SCIENCELOGIC™ AND ITS SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT.

Although ScienceLogic™ has attempted to provide accurate information on this Site, information on this Site may contain inadvertent technical inaccuracies or typographical errors, and ScienceLogic™ assumes no responsibility for the accuracy of the information. Information may be changed or updated without notice. ScienceLogic™ may also make improvements and / or changes in the products or services described in this Site at any time without notice.

Copyrights and Trademarks

ScienceLogic, the ScienceLogic logo, and EM7 are trademarks of ScienceLogic, Inc. in the United States, other countries, or both.

Below is a list of trademarks and service marks that should be credited to ScienceLogic, Inc. The ® and ™ symbols reflect the trademark registration status in the U.S. Patent and Trademark Office and may not be appropriate for materials to be distributed outside the United States.

- ScienceLogic™
- EM7™ and em7™
- Simplify IT™
- Dynamic Application™
- Relational Infrastructure Management™

The absence of a product or service name, slogan or logo from this list does not constitute a waiver of ScienceLogic's trademark or other intellectual property rights concerning that name, slogan, or logo.

Please note that laws concerning use of trademarks or product names vary by country. Always consult a local attorney for additional guidance.

Other

If any provision of this agreement shall be unlawful, void, or for any reason unenforceable, then that provision shall be deemed severable from this agreement and shall not affect the validity and enforceability of any remaining provisions. This is the entire agreement between the parties relating to the matters contained herein.

In the U.S. and other jurisdictions, trademark owners have a duty to police the use of their marks. Therefore, if you become aware of any improper use of ScienceLogic Trademarks, including infringement or counterfeiting by third parties, report them to Science Logic's legal department immediately. Report as much detail as possible about the misuse, including the name of the party, contact information, and copies or photographs of the potential misuse to: legal@sciencelogic.com. For more information, see <https://sciencelogic.com/company/legal>.

ScienceLogic

800-SCI-LOGIC (1-800-724-5644)

International: +1-703-354-1010