



Skylar One Juneau 12.5.7 Release Notes

Skylar One version 12.5.7

Skylar One Juneau 12.5.7 Release Notes

IMPORTANT: ScienceLogic strongly recommends that you review the [installation and upgrade instructions](#), [important upgrade notes](#), and [known issues](#) for this release before installing or upgrading to Skylar One 12.5.7.

The Skylar One Juneau 12.5.7 release includes package and security updates, as well as several optimization updates. It also addresses numerous issues from previous releases.

These release notes provide a comprehensive list of the features, enhancements, and addressed issues that are included in the Skylar One Juneau 12.5.7 release.

To view the updates that are included in previous Skylar One Juneau releases, see the following release notes:

- [12.5.1](#)
- [12.5.2](#)
- [12.5.3](#)
- [12.5.4](#)
- [12.5.5](#)
- [12.5.6](#)

NOTE: [AP2 version 8.26.4-45 \(Mochi\)](#) is installed by default in Skylar One 12.5.7.

This document covers the following topics:

Before You Proceed	3
New Features and Enhancements in Skylar One Juneau 12.5.7	4
Issues Addressed in Skylar One Juneau 12.5.7	5
Upgrading Skylar One	7
Important Upgrade Notes for Skylar One Juneau 12.5.7	7
Known Issues for Skylar One Juneau 12.5.7	13

Before You Proceed

If you are planning to consume Skylar One Juneau 12.5.7, be advised of the following:

- The 12.5.7 release is available only as a patch; there is no ISO version.
- All Python 2 functionality was removed from Skylar One with the 12.5.1 release. If you still use Python 2 for custom code, you cannot upgrade to this or any later releases until your custom code is Python 3-compatible.
- The validated upgrade paths to version 12.5.7 are outlined below. Be advised that you can perform upgrades from one minor version to any later minor version within the 12.5.x series. However, as with all updates, ScienceLogic strongly recommends that you perform such upgrades in a test environment before implementing the upgrades in production environments.
 - 12.5.6 > 12.5.7
 - 12.5.4 > 12.5.7
 - 12.5.1 > 12.5.7
 - 12.3.14 > 12.5.7
 - 12.3.7 > 12.5.7
- 12.5.x Juneau supports STIG deployments. However, STIG-compliant users should contact their ScienceLogic account managers for important information about upgrading to this release.
- AWS deployments that are using Aurora 3 can upgrade to this release.
- When upgrading Skylar One to version 12.5.7, PowerPacks will be temporarily read-only until the update is complete.
- The Enterprise Key Management Service (EKMS) is enabled by default in 12.5.7.

For more information, see the [Important Upgrade Notes](#) and [Known Issues](#) sections.

New Features and Enhancements in Skylar One

Juneau 12.5.7

This section describes the new features and enhancements that are included in Skylar One Juneau 12.5.7.

Platform and Security

- Skylar One version 12.5.7 includes package updates to improve security and system performance.

Skylar AI

- Made updates to optimize configuration data queries in the metadata exporter.

System Update

- Added a post-update script to clean up old patch bundles, which increases the amount of free space in the Database Server. During upgrades, the system will retain only the two most recent patches and remove all older ones.

TIP: This cleanup process might increase total deployment time for the initial cleanup when upgrading to Skylar One version 12.5.7, particularly on systems with a large number of older patch bundles. It takes approximately three to four minutes to clean up each patch; therefore, if you have 15 older patches that must be removed, for example, that can take an additional 45 to 60 minutes. To reduce upgrade time, you can optionally pre-clean older patches before upgrading using the command `silouupdate clear patches` on the active Database Server.

- Made enhancements to improve the patch import process. With this update, when you upgrade the system, the patch import status now gets marked as "Complete" immediately after the patch bundle is registered, which in turn starts the patch hook task.

Topology

- Updated the "Enterprise Database: Topology Crunch" process for better scaling.

Issues Addressed in Skylar One Juneau 12.5.7

This section describes the issues that were addressed in Skylar One Juneau 12.5.7.

Agent

- The agent summary period is now set to a default of 60 seconds, with the option to change it to up to 300 seconds. (Cases: 00589019, 00589175) (Jira ID: EM-78064)
- Improved the resilience of Windows CPU and disk data collection so the aggregator service is less likely to run out of memory. (Case: 00616233) (Jira ID: EM-78721)
- Ensured that Streamer Prime logs rotate correctly on Message Collectors and no longer fill `/var/log`. (Jira ID: EM-79217)
- Improved Responder Ingress handling so that it correctly obtains endpoints for services and avoids repeated "Error obtaining Endpoints for Service" messages. (Jira ID: EM-78710)

Data Collection and Retention

- Resolved an issue where a "Too Many Open Files" error from the Enterprise Database Collector Task Manager was raised as an event and system log message. (Case: 00613184) (Jira ID: EM-78660)
- Optimized the method by which SNMPv3 engine IDs are stored in the Database Server to lower write churn and overall load during normal polling. (Case: 00605594) (Jira ID: EM-79104)
- Resolved an issue where the daily maintenance process halted the pruning of expired data after it encountered an exception. (Case: 00619712) (Jira ID: EM-79102)
- Resolved an issue where interface data was not collected for tunnel or other interfaces without a physical address, despite interface index change detection being enabled for the device class. (Case: 00595591) (Jira ID: EM-78360)
- Addressed an issue that caused medium frequency data pull SQL syntax errors if a device sent empty processes data. (Jira ID: EM-78998)
- Resolved an issue that caused intermittent errors during legacy SNMP data collection for certain Dynamic Applications that used advanced syntax. (Jira ID: EM-78720)

Inbound Messaging

- Improved handling of unused or unparseable email headers so inbound email messages using Oracle UTL_MAIL packages can be processed correctly. (Case: 00604327) (Jira ID: EM-78456)

Reporting

- Ensured that interface aliases are included in exported "Network Utilization" reports for device interfaces. (Cases: 00520575, 00525158) (Jira ID: EM-79127)

Schedule Management

- Addressed an issue where non-recurring schedules created via the REST API did not display an end date in the **Schedule Manager** page for ServiceNow change requests. (Case: 00609709) (Jira ID: EM-78690)

Skylar AI

- Ensured that Skylar AI features remain enabled after a high-availability failover event without the need for manual intervention. (Jira ID: EM-78849)
- Optimized metadata exporter queries against large Dynamic Application database tables, significantly reducing export times and associated database load. (Case: 00623628) (Jira ID: EM-79051)

System Update

- Addressed an issue where manually running `silouupdate refresh-appliance` with an explicit `-m <mid>` option updated the Skylar One versions for appliances, even if the appliances had incomplete or failed deployment. (Jira ID: EM-77914)

Topology

- Link Layer Discovery Protocol (LLDP) relationships are now created only between devices whose interface information actually matches. (Cases: 00607249, 00624013) (Jira ID: EM-78532)

User Interface

- Updated the **License Data Delivery Status** page so that it displays only for secure deployments that use local crunching and are not connected to the Subscription Billing (V2) service. (Case: 00579464) (Jira ID: EM-79153)
- Updated the **Appliance Manager** page (System > Settings > Appliances) so you can change Data Collector configuration fields without being forced to re-enter an unchanged database password. (Jira ID: EM-79442)
- Ensured that the selection you make when uploading a file from the **Report Output Media** page (Reports > Management > Report Output Media) is correctly reflected in the **Upload an Image** modal. (Jira ID: EM-79381)
- Addressed an issue that caused an "unexpected EOF" error if you clicked the **[ARP Ping]** button from the **Device Toolbox** in the classic user interface. (Jira ID: EM-79077)
- Ensured that users can view the records for their assigned organizations on the **Device Processes** (Registry > Devices > Processes) and **Windows Services** (Registry > Devices > Services) pages in the classic user interface. (Case: 00544862) (Jira ID: EM-76329)

Upgrading Skylar One

IMPORTANT: You can consume Skylar One 12.5.7 only if you are upgrading from an earlier Skylar One version that *supports upgrades to this release*. There is no ISO version for version 12.5.7.

For a detailed overview of Skylar One, see the *Introduction to Skylar One* manual.

For detailed instructions on upgrading Skylar One, see the section on *Updating Skylar One* in the *System Administration* manual and the upgrade notes that are included in this document.

NOTE: ScienceLogic strongly recommends that you review the *Known Issues* for Skylar One at <https://support.sciencelogic.com/s/known-issues#sort=relevancy> before installing a new update.

For known issues specific to this release, see the *Known Issues* section of this document.

Skylar One Extended Architecture

For existing on-premises deployments of Skylar One Extended Architecture, see the section on *Upgrading Skylar One Extended Architecture* in the *System Administration* manual for upgrade instructions. For help with technical issues, contact ScienceLogic Customer Support.

NOTE: New installations of Skylar One Extended Architecture are available only on SaaS deployments.

Important Upgrade Notes for Skylar One Juneau 12.5.7

This section includes important notes for upgrading existing Skylar One systems to the Juneau 12.5.7 release.

Unless otherwise stated, the information in this section applies to all users who are upgrading from previous versions.

CAUTION: ScienceLogic strongly recommends that you review these notes in their entirety before upgrading to version 12.5.7.

Supported Upgrade Paths

The validated upgrade paths to version 12.5.7 are outlined below. Be advised that you can perform upgrades from one minor version to any later minor version within the 12.5.x series. However, as with all updates, ScienceLogic strongly recommends that you perform such upgrades in a test environment before implementing the upgrades in production environments.

- 12.5.6 > 12.5.7
- 12.5.4 > 12.5.7
- 12.5.1 > 12.5.7
- 12.3.14 > 12.5.7
- 12.3.7 > 12.5.7

NOTE: The 12.2.x Hollywood release line is now end-of-life. Direct upgrades from 12.2.x to version 12.5.4 or later are not validated.

NOTE: For more information about supported upgrade paths for Skylar One releases, see the [Skylar One Recommended Upgrade Paths](#) section in the *System Administration* manual.

Pre-Import Script for Upgrade Efficiency

Beginning with 12.5.1, the system update import experience was improved to make it faster and more efficient by allowing you to run concurrent imports. This feature is not enabled by default. To enable it, download the patch bundle you want to import, then run the following script:

```
silosql -e "INSERT INTO master.system_settings_patcher (param, value, description) VALUES ('use_concurrent_import', 1, 'Use concurrent patch import');"
```

After running the script, you can start the import process.

STIG Support

12.5.x Juneau supports STIG deployments. However, STIG-compliant users should contact their ScienceLogic account managers for important information about upgrading to this release.

NOTE: When deploying a STIG-compliant configuration, port 7700, the Web Configuration Utility, and the **Database Tool** page are all disabled. In addition, concurrent SNMP and concurrent network interface collection are not supported for these deployments.

Aurora 3 Support

AWS deployments that are using Aurora 3 can upgrade to Skylar One 12.5.7. If you are currently deployed using Aurora 2, you can upgrade to Skylar One 12.5.7 but must perform a post-upgrade Aurora 2 to 3 conversion. If you are on a SaaS-hosted AWS deployment, the ScienceLogic SRE team will complete this conversion. If you are on a customer-hosted AWS deployment, you must complete this conversion, with additional steps in the section on [Updating Skylar One](#) in the [System Administration](#) manual. Contact ScienceLogic Professional Services if you need assistance.

Upgrading MariaDB and Rebooting Skylar One

All Skylar One versions include important package security updates. To apply these updates, you must upgrade MariaDB and then reboot all Skylar One appliances. The following table specifies the required MariaDB version for each Skylar One version:

Skylar One (SL1) Release	Release Type	Required MariaDB Version
Juneau 12.5.7	Upgrade only	10.6.21
Juneau 12.5.6	Upgrade only	10.6.21
Juneau 12.5.5	Upgrade only	10.6.21
Juneau 12.5.4	ISO and upgrade	10.6.21
Juneau 12.5.3	Upgrade only	10.6.21
Juneau 12.5.2	Upgrade only	10.6.21
Juneau 12.5.1	ISO and upgrade	10.6.21
Ibiza 12.3.14	Upgrade only	10.6.18
Ibiza 12.3.13	Upgrade only	10.6.18
Ibiza 12.3.12	Upgrade only	10.6.18
Ibiza 12.3.11	ISO and upgrade	10.6.18
Ibiza 12.3.10	Upgrade only	10.6.18
Ibiza 12.3.9	Upgrade only	10.6.18
Ibiza 12.3.8	Upgrade only	10.6.18
Ibiza 12.3.7	ISO and upgrade	10.6.18
Ibiza 12.3.6	Upgrade only	10.6.18
Ibiza 12.3.5	Upgrade only	10.6.18
Ibiza 12.3.4	Upgrade only	10.6.18
Ibiza 12.3.3	Upgrade only	10.6.18
Ibiza 12.3.2	Upgrade only	10.6.18
Ibiza 12.3.1	ISO and upgrade	10.6.18
Ibiza 12.3.0	ISO and upgrade	10.6.18

NOTE: For instructions on updating MariaDB or rebooting the Skylar One system, see the section on [Updating Skylar One](#) in the [System Administration](#) manual.

If you would like assistance in planning an upgrade path that meets your security needs while minimizing downtime, please contact your Customer Success Manager.

Clearing Cache Post-Upgrade

After upgrading to version 12.5.7, you should clear your system cache to remove cached items from Skylar One (SL1) and prevent several potential issues that can occur post-upgrade due to caching. To do so, go to Misc > Clear SL1 Cache.

Required Ports

Beginning with SL1 12.2.0, if you have a firewall between your Database Server, data engine, and Administration Portal appliances, you should open TCP port 8200 to facilitate communication between those appliances.

For a full list of ports that must be open on each Skylar One (SL1) appliance, see the section on [Required Ports for Skylar One](#) in the [Installation and Initial Configuration](#) manual.

Python 3.9 Execution Environment Support Deprecation

Users who are currently on 12.2.x releases and use Python 3.9 execution environments for Dynamic Applications and Run Book Automations are advised that the 12.3.0 Ibiza release removed support for Python 3.9 and added support for Python 3.11. For more information, see the section [Important Notes on Creating ScienceLogic Libraries](#) in the [ScienceLogic Libraries and Execution Environments](#) manual.

Use of tmux When Using SSH

Starting with Skylar One (SL1) version 12.3.4, the tmux utility is disabled by default if you are on a non-STIG deployment and access a Skylar One (SL1) system using SSH. ***This is a change in behavior from versions 12.2.1.1 through 12.3.3, where the tmux utility was enabled by default.***

If you are on a STIG-compliant Skylar One (SL1) deployment, the tmux utility is enabled by default. ScienceLogic encourages non-STIG users to enable the tmux utility as well.

The utility, which is a terminal multiplexer that enables a number of terminals to be created, accessed, and controlled from a single screen, strengthens session-control mechanisms and aligns with industry-wide security practices.

If tmux is enabled, sessions are automatically locked after 15 minutes of idleness or if an unclean SSH disconnect or dropped SSH connection occurs. Upon login, Skylar One (SL1) checks for and attaches any detached tmux session if it finds them; otherwise, it starts a new session.

The utility also facilitates advanced features like scroll-back buffering with search, built-in clipboarding, multiple sessions and panes, detaching or attaching sessions, and session supervision or sharing.

To enable the tmux utility in non-STIG deployments:

1. Either go to the console of the Skylar One (SL1) appliance or use SSH to access the appliance.
2. Open a shell session on the server.
3. Type the following at the command line to edit the `silo.conf` file:

```
sudo visilo
```

4. Change the following line in the `[OS_HARDENING]` section of the file to enable tmux:

```
TMUX = true
```

NOTE: If the `[OS_HARDENING]` heading does not already exist in the `silos.conf` file, you must add that immediately above the `TMUX = true` setting.

5. Save and quit the file. (`:wq`).
6. Log out of Skylar One (SL1) and then log back in. The tmux utility is now enabled.

For more information about tmux shortcuts and usage, see <https://tmuxcheatsheet.com/>.

Changes to High Availability and Disaster Recovery Configurations

In Skylar One (SL1) 12.3.2, the web server configuration for the vault service was updated to improve behavior between multiple database and data engine appliances. This was done to prevent false system events indicating that passive databases could not connect to Skylar One Collectors in high-availability (HA), disaster recovery (DR), or HA+DR configurations. With this update:

- On new installations, you must run the following command after all database and data engine appliances are licensed, to populate the list of allowed locations where vault could be running: `sudo /opt/em7/share/scripts/vault_add_servers.sh`. If the list is populated successfully, the output will tell you to restart nginx for it to take effect. Upon updating, this is generated automatically.
- If you are upgrading and you have not modified the default configuration file, then it will be updated to this new configuration automatically.
- If you are upgrading and you have modified the default configuration file, the updated web server configuration will be installed as `/etc/nginx/conf.d/vault.conf.rpmnew`, and you will need to merge your modifications into the new configuration and then remove the `.rpmnew` extension.

System Update Notes

- **Skylar One updates overwrite changes to the configuration file `/opt/em7/nextui/nextui.env`.** (For more details, see <https://support.sciencelogic.com/s/article/1423>.) ScienceLogic recommends that you back up this file before applying an update and then reapply your changes to this file.
- ScienceLogic recommends that you run backups of your Skylar One system before performing a system update.

- The Skylar One user interface will be unavailable intermittently during system update.
- During the normal system update process, multiple processes are stopped and restarted. This might result in missed polls, gaps in data, and/or unexpected errors. ScienceLogic recommends that you always install Skylar One releases during a maintenance window.
- The Skylar One system update process starts a background process that can perform any required post-upgrade tasks. The post-patch update process is automatically stopped after 24 hours. However, depending on the size of your database as well as the version from which you are upgrading, the post-upgrade tasks can take several days to perform. If the post-patch update process is stopped after 24 hours, the process will automatically re-start and continue processing from the point at which it was stopped. If you see an event that indicates the post-patch update process was stopped, you do not need to contact ScienceLogic support for assistance until you see the same event for three consecutive days.
- When upgrading a large number of Skylar One appliances, you might encounter an issue where the deployment summary shows that deployment timed out for many of the appliances but, upon further inspection, you discover that the appliances actually deployed correctly. This is due to a lag in the deployment status reaching the Database Server after the default timeout value of 3600 seconds (1 hour). If you check back later, the issue should fix itself. If you would rather work around this issue, you can increase the timeout value. For instructions, see the section on [Adjusting the Timeout for Slow Connections](#) in the "[Updating Skylar One](#)" chapter of the **System Administration** manual.
- When upgrading Skylar One on AWS stacks, you might receive an error message that the Data Engines failed to patch correctly. If this occurs, re-run the pre-upgrade tests and then run the patch again; this should result in the Data Engines updating correctly and the correct version then being reflected on the **Appliance Manager** page (System > Settings > Appliances).
- After upgrading, to ensure proper data collection, you should go to the **Appliance Manager** page (System > Settings > Appliances), locate one of the Data Collector or Message Collector appliances, and click the lightning bolt icon to force configuration push for that appliance.

Known Issues for Skylar One Juneau 12.5.7

NOTE: ScienceLogic strongly recommends that you review all [Known Issues](#) for Skylar One. For more information, see <https://support.sciencelogic.com/s/known-issues#sort=relevancy>.

The following known issues exist for Skylar One Juneau 12.5.7:

Deployment and Configuration

- After deploying or upgrading to Skylar One Juneau 12.5.7, you might not be able to log in to the Web Configuration Utility or port 7700. To resolve this issue, reboot the Data Engine or restart the `em7_sladmin` service. (Jira ID: EM-78175)

System Upgrade

- Support for Python 2 is deprecated in Skylar One as of the 12.5.1 release. Any custom Python 2 content you have developed will stop working if you upgrade to 12.5.1 or later. This includes all Dynamic Application snippets, Execution Environments, Run Book Actions, and ScienceLogic Libraries that use Python 2. These items must be recreated utilizing ScienceLogic-provided enablement tools or migrated to Python 3 **before** you upgrade to this release.
- 12.2.x and 12.3.x STIG-compliant users should contact their ScienceLogic account managers for information about upgrading to this release.
- When upgrading Skylar One to version 12.5.7, PowerPacks will be temporarily read-only until the update is complete. (Jira ID: EM-73018)
- Importing a patch bundle with `use_concurrent_import` enabled might result in a "no space left on device" error. (Jira ID: EM-79357)
- In systems that have consumed a large number of Skylar One (SL1) patch imports, the `master_filestore.storage_system_patch` database table might grow too large in size. If this occurs, then when you attempt to log in to Skylar One, you will be unable to do so and will instead receive an error message stating "The table 'organizations_log' is full" if logging in via the default user interface (AP2), or without an error message if logging in via the classic user interface. To address this issue, you should clean up any previous patch import files after deploying a new version on your Skylar One stack. For more information about this issue, see <https://support.sciencelogic.com/s/article/18285>. (Jira ID: EM-76040)
- System updates sometimes fail on Data Collectors due to silouupdate not updating on them. For more information about this issue, including workaround procedures, see <https://support.sciencelogic.com/s/article/18508>. (Case: 00543539) (Jira ID: EM-76307)
- After updating your system, you might experience an issue where the user interface is not displaying or working as intended. If this occurs, clear your browser cache. (Jira ID: EM-73859)

- An intermittent issue sometimes causes the database connection to Amazon RDS instances to become unavailable for a brief amount of time during the upgrade process, which causes deployment to be marked as failed in the user interface. If this occurs, re-run the upgrade; doing so should update all backend metadata to register as successfully completed and update the latest version in the user interface. (Jira ID: EM-66627)

Agent

- Clicking the **[Upgrade]** button on the **Agents** page results in a message indicating that the upgrade was successful immediately appearing at the bottom of the page when, in actuality, the upgrade was merely initiated. The actual upgrade process can take several minutes to complete. (Jira ID: EM-74365)
- When attempting to install a Gen 1 agent on an AWS stack, the installation user interface will display an incorrect IP for download, which will result in the download attempt failing. (Jira ID: EM-74307)
- You might experience a scenario where an agent's polled data configuration is cleared unintentionally. (Jira ID: EM-74364)

API

- Deleting a user account via the REST API (`DELETE /api/account/<uid>`) does not archive the account in the `master_access.accounts_deleted` database table, thus allowing the next account created to reuse the deleted account's user ID (uid). (Jira ID: SLS-2044)

Asset Management

- When creating or editing an asset, the values entered in the **Administrator** and **Technician** fields might not be saved. (Jira IDs: EM-74258, EM-76664)

Authentication

- A known issue with session cache management might cause Skylar One to log you out unexpectedly, or prevent you from logging in again after a recent session. If you experience either issue, you can work around it by clearing the cache of your web browser before you log into the Skylar One user interface. For more information, see <https://support.sciencelogic.com/s/article/13701>. (Jira ID: SLUI-21011)
- The **Single Instance Login** setting, which can be set on the **Behavior Settings** page (System > Settings > Behavior), is not working as designed for local non-administrator user accounts that utilize CAC or ADFS authentication. (Jira IDs: SLS-1559)
- If you create an empty authentication resource with no values filled in and assign it to an empty authentication profile, upon logging out of the system, the user interface becomes inaccessible. (Jira ID: EM-76608)

Business Services

- The **[Anomalies]** tab on the **Service Investigator** page for device services might incorrectly display devices that have anomaly detection disabled, rather than showing only those devices with anomaly detection enabled. (Jira ID: EM-62884)
- For services that have their **RCA Options** field enabled and have had a child service removed, Skylar One will not compute the health, availability, and risk values until the Service Topology Engine returns an updated topology, which occurs every 5 minutes by default. (Jira ID: SLUI-18853)

IMPORTANT: Before deleting child services in a 3-tier hierarchy, check if the parent service has the **RCA Options** field *Enabled*, then set this field to *Disabled* if it is not already.

Collector Groups

- If you have a collector group (CUG) with just one collector unit that has devices aligned to it, a user can remove the lone collector from the group, leaving the collector group with no collectors and the devices no longer aligned to a collector. (Jira ID: EM-79578)

Credential Management and Discovery

-
- You might experience an issue retrieving universal credentials, which prevents you from running backups from Disaster Recovery nodes. (Jira ID: EM-78993)
- For an unguided device discovery, the **Search** box that displays for creating a new credential does not work. (Jira ID: SLUI-20777)
- When using the SNMP Public V2 credential to discover devices, you might see an unhandled exception in the system log near the end of the discovery session, despite the devices being discovered successfully. (Jira ID: EM-59380)
- When selecting two or more SNMP credentials to discover a device, if the first credential with the lower ID number contains incorrect information and the second credential with a higher ID number contains the correct information, the discovery logs will not be able to get an SNMP response. (Cases: 00289639, 00292649, 00422558) (Jira ID: EM-39681)
- The **Credentials** page in the default user interface (AP2) fails to display credentials that are not aligned with an organization, but displays these credentials correctly in the classic Skylar One user interface on the **Credential Management** page. (Jira ID: SLUI-20947)
- On the **Credentials** page, if you have more than 50 credentials and at least one of the first 50 credentials is not aligned with an organization, the page will display duplicates of these credentials. (Jira ID: SLUI-20947)
- On systems with healthy EKMS installations enabled on a passive node, or in systems where EKMS is disabled altogether, the `slsctl health_check` might mistakenly return a `failure` value. (Jira IDs: SLS-1404)

- When attempting to discover Oracle devices with Native Network Encryption (NNE) enabled or using secure communication (TCPS), you might receive an error stating that the system failed to initialize Oracle Instance Client libraries, preventing those devices from being discovered. (Jira ID: EM-74110)
- You might get an error when trying to open SOAP/XML credentials that have been imported from a PowerPack. (Jira ID: EM-74291)
- You might experience an issue where the EKMS state and vault contents disappear from your Data Collectors. If this occurs, you can work around the issue by going to the **Appliance Manager** page (System > Settings > Appliances) and manually running the **Enterprise Database: Collector Config Push** process to run on the impacted appliances. (Jira ID: EM-78522)

Dashboards

- In dashboards created in the default user interface (AP2), Devices and File Systems widgets might display incorrect data due to a known mathematic scaling issue. To work around this issue, consult the same metrics in the **[Performance Metrics]** tab of the **Device Investigator**, or in the **[Performance]** tab of the **Device Reports Panel** in the classic user interface. (Jira ID: EM-79597)
- Creating an **Interface** widget with the *Leaderboard* visualization, applying an advanced filter, and adjusting the data time span using the **Time span filter** results in an error. (Jira ID: SLUI-22200)
- When editing the scale prefix of a **Device** widget using the *Leaderboard* visualization, the **Storage Used** column does not update in that widget's table. (Jira ID: SLUI-22198)
- When editing an **Events** widget and setting the **Refresh Mode** field to *None*, the widget's events table shows the refresh mode as automatic, despite the change. (Jira ID: SLUI-21947)
- In classic dashboards, if you create a Traffic Light widget, the ability to control context in other subscribing widgets is not working as intended. (Jira ID: EM-76527)
- Classic dashboard reports cannot be scheduled. Attempting to do so results in a "report is blank" error appearing in the system log. (Jira ID: EM-61778)

Data Collection and Retention

- If you include an invalid or incorrectly typed value in `silos.conf`, such as a word or phrase where it should be an integer, the data pull process crashes and cannot start. (Jira ID: EM-74238)
- When aligning a Dynamic Application that discovers a dynamic component map tree using Latin-1 and UTF-8 encoded device names and identifiers, you might receive "Illegal mix of collations" data storage errors in the system logs. (Jira ID: EM-74263)

Device Management

- Clicking the printer icon to print a report on either the **Device Processes** page (Devices > Processes) or **Windows Services** page (Devices > Services) results in a blank page appearing rather than a modal of report options. To work around this issue, go to the **Classic Devices** page (Devices > Classic Devices), click the bar graph icon for the device you want to print a processes or services report for, select either the **[Process]** tab or **[Services]** tab, and then click the printer icon. (Case: 00503774) (Jira ID: EM-73062)

- On the **Devices** page, when sorting your search by the **Organization** column, the inventory table will sort by **Organization ID** instead. (Jira ID: SLUI-21459)
- The assigned organization for devices might not always update, even after performing a bulk alignment organization action on the **Devices** page. To work around this issue, refresh your browser immediately after completing the bulk alignment action. (Jira ID: SLUI-21483)
- The column widths on the **Device Investigator** page do not adjust when resized. (Jira ID: SLUI-20081)
- Filtering the **Collector Groups** column on the **Device Investigator** page with multiple group names can cause the page to not load correctly. (Jira ID: SLUI-21035)
- When sorting by columns on the **Device Investigator** page in Firefox, the table might continuously attempt to retrieve results unsuccessfully. (Jira ID: SLUI-21095)
- The **Device Categories** page (Devices > Device Categories) fails to load properly whenever there is a category with a null ID. To work around this issue, go to the **Device Categories** page (System > Customize > Device Categories), locate the category with the null ID, and then remove that category by clicking the delete icon (🗑️) next to the category. (Jira ID: SLUI-20731)
- The number of unacknowledged events in the **Device Overview** panel of the **Device Investigator** page does not update despite acknowledging alerts on a device. To work around this issue, add a new "unackEvents" subquery to the "Device Insights" query, then use that subquery to collect and retrieve information on unacknowledged events. (Case: 00471966) (Jira ID: SLUI-20858)
- When attempting to bulk delete devices or device components, a dialog message might indicate that some or all of the devices or components failed to delete, when in fact they were actually deleted. (Jira ID: EM-74351)
- Device reports generated from the **Classic Devices** page (Devices > Classic Devices) might result in an "Uncaught TypeError" message appearing in the browser console, despite most reports generating correctly. (Jira ID: EM-74225)
- HTML device journal reports might generate with no data. (Jira ID: EM-74286)
- The checkbox to select all items on the **Device Dashboards** page (System > Customize > Device Dashboards) might select only the items that appear on your current page rather than all available device dashboards. (Jira ID: EM-74215)
- Event messages in device logs for multi-match events might display with the incorrect event ID . Additionally, the device logs might not indicate how many times an event has repeated. (Jira IDs: EM-74409, EM-74381)

Enterprise Key Management Service (EKMS)

- In some EKMS configurations, re-running firstboot on an already initialized system can result in a firstboot script that never completes. (Jira ID: SLS-1974)

Events and Alerts

- Deviation alerting does not support the use of double quotes in indices. To work around this issue, use single quotes. (Jira ID: EM-72050)
- The events on the **Events** page cannot be sorted by the **Organization** column. (Jira ID: SLUI-20903)

- From the **Event Policies** page (Events > Event Policies), you can delete only a single event policy at a time, even if you select multiple event policies for bulk deletion. (Jira ID: SLUI-20853)
- Event messages derived from incoming email substitute "\xc2" for the character Â. (Jira ID: EM-73551)

Global Manager

- The devices on the **Devices** page in Global Manager systems cannot be sorted by the *IP Address* column. (Jira ID: SLUI-21108)
- On Global Manager systems, the *View Event Policy* option in the **Actions** menu (⋮) on the **Events** page does not work as expected. (Jira ID: SLUI-21133)
- On Global Manager systems, the **Events** page does not display events from child stacks. To work around this issue, clear all system caches on both the child stacks and the Global Manager parent stack, then restart the NextUI service. (Jira ID: SLUI-21134)

GraphQL

- The "harProviderOnDemanProcessing" GQL query incorrectly creates a service table in the "data_har" database when executed with invalid or non-existent service IDs. (Jira ID: SLUI-21135)
- Clicking the **[Run Now]** button for any Dynamic Application on the **[Collections]** tab of the **Device Investigator** will display the following GQL error message in the Skylar One server console: "Variable "\$proclD" of non-null type "ID!" must not be null." (Jira ID: SLUI-21070)

High Availability and Disaster Recovery

- When EKMS is enabled in a high-availability (HA) configuration, the EKMS vault service might be unable to start after a failover due to bad configuration files. This issue is seen when a user has a working HA setup configuration, then later re-ISOs or rebuilds one of the Database Servers. One source of the rebuilt Database Server is swapping active node with DR node. For more information about this issue, see <https://support.sciencelogic.com/s/article/15486>. (Jira ID: SLS-1341)

Logging

- A known issue might cause several log configuration files to conflict, which could cause you to see errors for the `sl_vault` and `slsctl` logs or potentially block log rotation in some cases, depending on the order in which the files are executed. To work around this issue, delete the config files `~sl_vault` and `~slsctl`. (Jira IDs: SLS-1105, EM-62134)

PowerPacks

- When upgrading, PowerPacks will be temporarily read-only until the update is complete.
- In STIG deployments, you might not be able to add AP2 content objects to PowerPacks. (Jira ID: EM-78797)

- Due to a known issue, you might need to manually upgrade to the following PowerPack versions after installing or upgrading to Skylar One 12.5.1 or later:
 - "Net-SNMP Base Pack" PowerPack v103 (Jira ID: EM-73518)
 - "Microsoft Base Pack" v110 (Jira ID: EM-73516)
 - "Microsoft: Windows Server" v118 (Jira ID: EM-73516)
- When installing or importing a PowerPack, you might not be able to adjust the PowerPack's embedded license or license key type. (Jira IDs: EM-71507, EM-72515, EM-72716)

Reporting

- A new, non-administrator user that has all of the Reporting access keys aligned to their user account cannot create a new scheduler or see the archived reports. (Jira ID: EM-72259)
- Reports that include images or charts fail to generate properly in ODS format. (Jira ID: EM-75401)
- Some information from the Device Combo report might not appear at the top of the generated report output. (Jira ID: EM-74144)
- If you create a PDF report about a single device from the **Devices** or **Classic Devices** pages (Devices > Classic Devices, or Registry > Devices > Device Manager in the classic user interface), some tables might not display as intended. (Jira ID: EM-79587)

Schedule Management

- A large number of stored procedure calls over time can lead to memory growth in the scheduler process as well as delays in processing schedules. (Jira ID: EM-76720)

Skylar AI

- The `sl-otelcol-mgmt.py` script shows blank values for the `sl-otelcol`, `em7-platform-core`, and `nextui` versions when connecting to Skylar AI, making it unclear which versions are actually installed, even though the status output reports the versions correctly. (Jira ID: EM-78655)
- Skylar AI Connection debug always runs on the node the connection was initially configured with, even after a failover. When this occurs, it causes a false negative status. (Jira ID: EM-78209)
- Supplying an open telemetry collector endpoint URL with a trailing slash can cause the endpoint to be rejected or fail validation. As a workaround, remove any trailing slash from the URL before saving. (Jira ID: EM-77859)

System Administration

- When editing a collector group from the **Collector Groups** page (Manage > Collector Groups) by clicking its **Actions** menu (ellipsis icon) and unchecking two or more organizations in the **Limit access to specific organizations** field of the **Edit Collector Group** modal, the **Organizations** column on the **Collector Groups** page will show that only one organization was deselected, even if multiple were. (Jira ID: SLUI-22167)
- Message Collectors on the **Collector Groups** page (Manage > Collector Groups) cannot be sorted by the **Message Collectors** column. (Jira ID: SLUI-22099)

User Interface

- In the Skylar One user interface, the End User License Agreement (EULA) page is displayed on all pages that were iframed from the classic user interface, even after the user agrees to the EULA. This issue is occurring for ADFS, CAC, and AD authentication methods. (Jira ID: EM-67851)
- After upgrading to 12.3.2 or later, custom themes and logos might not display on classic user interface pages. To work around this issue, clear the cache of your web browser. (Case: 00503523) (Jira ID: EM-72921)
- The **[Expand]** and **[Contract]** buttons are not working as intended on the **Dynamic Application Collections** page (Devices > Device Manager > wrench icon > Collections). You can still expand and contract individual items on the page. (Jira ID: EM-64420)
- The **Access Keys** page (System > Manage > Access Keys) might not count administrator users in the value displayed in the **# Aligned Users** column. To work around this issue, go to the **Account Permissions** page (Registry > Accounts > User Accounts > wrench icon) for the administrator users and re-save their permissions. (Jira ID: EM-74241)
- When you bulk-select multiple event policies to align with a run book automation policy, additional event policies that you did not select might become aligned with that automation policy as well. (Jira ID: EM-70690)
- On the **Admin Processes** page (System > Settings > Admin Processes), the **Runtime Offset** column does not display any values. You can view the runtime offset value by editing the process. (Case: 00506663) (Jira ID: EM-73218)
- On the **Custom Attributes** page (Manage > Custom Attributes), you might not be able to view more than the first 20 custom attributes unless you zoom in or change the size of your browser to force Skylar One to fetch additional attributes. You also might not be able to select the "Select All" checkbox on the page. (Jira IDs: SLUI-21449, EM-74251)
- Name changes to nodes on the **Nodes** page (Manage > Nodes) are not saved. (Jira ID: SLUI-22248)
- In the default user interface (AP2), when opening the **Account Permissions** page (Registry > Accounts > User Accounts > wrench icon) for an existing user account, the **Theme/Brand** drop-down field does not initially display on the page. To work around this issue, refresh the page. (Jira ID: EM-76478)
- On the **OID Browser** page (System > Tools > OID Browser), the *Where Symbolic is like* drop-down option for the **Search where** field might not work as intended. (Jira ID: EM-74326)
- In the classic user interface, the filter for **Edit Date** is not working as intended on the **Inbound Email** page (Registry > Events > Inbound Email). (Jira ID: EM-75291)
- When using a dark mode theme, if you click on a calendar icon to select a date, some dates might not be visible on the calendar. (Jira ID: EM-76629)
- The final row might not appear on the **Select Objects** page (System > Customize > Select Objects) when viewed in the default user interface (AP2) using a Firefox browser. (Jira ID: EM-74222)
- When using Active Directory Federation Services (ADFS) to authenticate, the system opens to the default landing page rather than the last page the user visited. (Jira IDs: SLS-1764, SLS-1765)
- If you create a new network on the **IPv4 Networks** page (Registry > Networks > IPv4 Networks), it might not appear on the page after you save it. However, the network should still be available for selection in other operations. (Jira ID: EM-76666)

- In AWS deployments, the **% Used** column on the **IPv4 Networks** page (Registry > Networks > IPv4 Networks) might erroneously display values over 100%. (Jira ID: EM-76672)
- When saving a change on the **Quality of Service Threshold Defaults** page (System > Settings > Thresholds > Quality of Service), the page might continuously state that it is saving until you refresh the page. Despite this messaging issue, the system should save the changes correctly. (Jira ID: EM-74336)
- If you select a normalized option for a service usage graph, the **Date Range Selection** pane changes to the year 1970 and the graph will not be visible, even if you correct the start and end dates. (Jira ID: EM-74331)
- When creating an uptime OID, the system might display an error alert if the OID is invalid but still save the OID anyway. (Jira ID: EM-74227)
- On the **Process Manager** page (System > Settings > Admin Processes), if you deselect the appliance type(s) that a process should run on and then save that change, it will prevent that process from starting in the future. (Jira ID: EM-74236)
- If you click the **[Save]** button on the **User Policy Properties Editor** page (Registry > Accounts > User Policies > create or edit) for an existing user policy, the system mistakenly saves the user policy again as a separate entry rather than overwriting the existing policy with the updated information. (Jira ID: SLS-1773)
- When adding a new Access Key on the **Key/Hook Alignment Editor** page (System > Manage > Access Keys > Key Manager), the form might not reset if you click the **[New]** button. (Jira ID: EM-76407)

Known Issues Resolved in Available Releases

The following known issues impacting this release are fixed if you upgrade to the [AP2 version 8.29.41 \(Nougat\)](#) release or later **after** upgrading to 12.5.7:

- If you are running AP2 version 8.26.4-45 (Mochi), you might experience a "red bell" error on the **Credentials** page, indicating that the page cannot load. This occurs when a credential GUID length is less than 32 characters. To work around this issue, recreate the credential with the incorrect GUID length, realign all impacted Dynamic Applications and Run Book Automations to that new credential, and then delete the original credential. (Cases: 00568449, 00568858) (Jira ID: EM-77246)
- The **[Edit Note]** button on the **Events** page does not work when multiple events are selected for editing notes in Global Manager. (Jira ID: SLUI-21131)

The following known issue impacting this release is fixed if you upgrade to the [AP2 version 8.34.20 \(Opera Cake\)](#) release or later **after** upgrading to 12.5.7:

- When creating or editing a credential, the **Select Credential Test** field in the **Credential Tester** panel might display only a small number of potential credential tests rather than the full list. (Jira ID: SLUI-22754)

© 2003 - 2026, ScienceLogic, Inc.

All rights reserved.

ScienceLogic™, the ScienceLogic logo, and ScienceLogic's product and service names are trademarks or service marks of ScienceLogic, Inc. and its affiliates. Use of ScienceLogic's trademarks or service marks without permission is prohibited.

ALL INFORMATION AVAILABLE IN THIS GUIDE IS PROVIDED "AS IS," WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED. SCIENCELOGIC™ AND ITS SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT.

Although ScienceLogic™ has attempted to provide accurate information herein, the information provided in this document may contain inadvertent technical inaccuracies or typographical errors, and ScienceLogic™ assumes no responsibility for the accuracy of the information. Information may be changed or updated without notice. ScienceLogic™ may also make improvements and / or changes in the products or services described herein at any time without notice.

Copyrights and Trademarks

ScienceLogic, the ScienceLogic logo, and EM7 are trademarks of ScienceLogic, Inc. in the United States, other countries, or both.

Below is a list of trademarks and service marks that should be credited to ScienceLogic, Inc. The ® and ™ symbols reflect the trademark registration status in the U.S. Patent and Trademark Office and may not be appropriate for materials to be distributed outside the United States.

- ScienceLogic™
- EM7™ and em7™
- Simplify IT™
- Dynamic Application™
- Relational Infrastructure Management™

The absence of a product or service name, slogan or logo from this list does not constitute a waiver of ScienceLogic's trademark or other intellectual property rights concerning that name, slogan, or logo.

Please note that laws concerning use of trademarks or product names vary by country. Always consult a local attorney for additional guidance.

Other

If any provision of this agreement shall be unlawful, void, or for any reason unenforceable, then that provision shall be deemed severable from this agreement and shall not affect the validity and enforceability of any remaining provisions. This is the entire agreement between the parties relating to the matters contained herein.

In the U.S. and other jurisdictions, trademark owners have a duty to police the use of their marks. Therefore, if you become aware of any improper use of ScienceLogic Trademarks, including infringement or counterfeiting by third parties, report them to Science Logic's legal department immediately. Report as much detail as possible about the misuse, including the name of the party, contact information, and copies or photographs of the potential misuse to: legal@sciencelogic.com. For more information, see <https://sciencelogic.com/company/legal>.

ScienceLogic

800-SCI-LOGIC (1-800-724-5644)

International: +1-703-354-1010